





Version: V1 2021-04-21

 +86-754-85751187

 +86-754-85300887

 info@nanlux.com

 Zhanglin,324,Dongli Chenghai Shantou Guangdong China

Guangdong NanGuang Photo&Video Systems Co., Ltd



WWW.NANLUX.COM



DMX EFFECT CHART	
EFFECT	WELDING 181 ≤ value ≤ 198
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	PAUSE: OFF = 0-127(0%-50%) PAUSE: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

CATALOG

DAYLIGHT 8bit ..... 01

ULTIMATE DMX 8bit - DAYLIGHT MODE ..... 01

ULTIMATE DMX 8bit - EFFECT MODE ..... 02

DMX EFFECT CHART

INT LOOP ..... 04

FLASH ..... 05

PULSE ..... 05

STORM ..... 06

TV ..... 07

PAPARAZZI ..... 07

CANDLE/FIRE ..... 08

BAD BULB ..... 09

FIREWORK ..... 09

EXPLOSION ..... 10

WELDING ..... 11

DAYLIGHT 8bit				
CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-127 128-255	0-50 51-100	FAN ON FAN OFF	
ULTIMATE DMX 8bit - DAYLIGHT MODE				
CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE DAYLIGHT EFFECT RESERVED	0 ≤ value ≤ 63
3-9			N/A	

DMX EFFECT CHART		
EFFECT	EXPLOSION 163 ≤ value ≤ 180	
CH4/PARAMETER #1	DECAY	
CH5/PARAMETER #2	TRIGGER: AUTO = 0-127[0%-50%]	TRIGGER: MANUAL = 128-255[51%-100%]
CH6/PARAMETER #3	SPEED	Trigger: OFF = 0-127[0%-50%] Trigger: ON = 128-255[51%-100%]
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART	
EFFECT	BAD BULB 127 ≤ value ≤ 144
CH4/PARAMETER #1	INTENSITY
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
DMX EFFECT CHART	
EFFECT	FIREWORK 145 ≤ value ≤ 162
CH4/PARAMETER #1	SPEED
CH5/PARAMETER #2	DECAY
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

ULTIMATE DMX 8bit - EFFECT MODE				
CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0.0% to 100.0%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE DAYLIGHT EFFECT RESERVED	64 ≤ value ≤ 127
3	0-18 19-36 37-54 55-72 73-90 91-108 109-126 127-144 145-162 163-180 181-198 199-255	0-7 8-14 15-21 22-28 29-35 36-42 43-50 51-57 58-64 65-71 72-78 79-100	EFFECT MODE INT LOOP FLASH PULSE STORM TV PAPARAZZI CANDLE/FIRE BAD BULB FIREWORK EXPLOSION WELDING RESERVED	

ULTIMATE DMX 8bit - EFFECT MODE				
CHANNEL	VALUE	%	FUNCTION	NOTES
4	0-255	0-100	DMX EFFECTS PARAMETER #1	See DMX Effects chart
5	0-255	0-100	DMX EFFECTS PARAMETER #2	See DMX Effects chart
6	0-255	0-100	DMX EFFECTS PARAMETER #3	See DMX Effects chart
7	0-255	0-100	DMX EFFECTS PARAMETER #4	See DMX Effects chart
8	0-255	0-100	DMX EFFECTS PARAMETER #5	See DMX Effects chart
9	0-255	0-100	DMX EFFECTS PARAMETER #6	See DMX Effects chart
10	0-127 128-255	0-50 51-100	FAN ON FAN OFF	

DMX EFFECT CHART	
EFFECT	CANDLE/FIRE 109 ≤ value ≤ 126
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	FLICKER: OFF = 0-127[0%-50%] FLICKER: ON = 128-255[51%-100%]
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART	
EFFECT	TV 73 ≤ value ≤ 90
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
DMX EFFECT CHART	
EFFECT	PAPARAZZI 91 ≤ value ≤ 108
CH4/PARAMETER #1	SPEED
CH5/PARAMETER #2	N/A
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A

DMX EFFECT CHART				
EFFECT	INT LOOP 0 ≤ value ≤ 18			
CH4/PARAMETER #1	DIM LOW			
CH5/PARAMETER #2	SPEED			
CH6/PARAMETER #3	CYCLE: ONE WAY = 0-85[0%-33%] CYCLE: TWO WAY = 86-170[34%-66%] CYCLE: REVERSE = 171-255[67%-100%]			
CH7/PARAMETER #4	ADD-ON: OFF = 0-63[0%-25%]	ADD-ON: FLASH = 64-127 [26%-50%]	ADD-ON: RANDOM FLASH = 128-191[51%-75%]	ADD-ON: PULSE = 192-255 [76%-100%]
CH8/PARAMETER #5	N/A	INTERVALS	SPEED	PULSES/MIN
CH9/PARAMETER #6	N/A	FLASH RATIO	N/A	N/A

DMX EFFECT CHART		
EFFECT	FLASH 19 ≤ value ≤ 36	
CH4/PARAMETER #1	INTERVALS	
CH5/PARAMETER #2	FLASH RATIO	
CH6/PARAMETER #3	PAUSE: OFF = 0-127(0%-50%)	PAUSE: ON = 128-255(51%-100%)
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART		
EFFECT	PULSE 37 ≤ value ≤ 54	
CH4/PARAMETER #1	PULSES/MIN	
CH5/PARAMETER #2	N/A	
CH6/PARAMETER #3	N/A	
CH7/PARAMETER #4	N/A	
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	

DMX EFFECT CHART		
EFFECT	STORM 55 ≤ value ≤ 72	
CH4/PARAMETER #1	FLASH TIMES HIGH	
CH5/PARAMETER #2	FLASH TIMES LOW	
CH6/PARAMETER #3	TRIGGER: AUTO = 0-127[0%-50%]	TRIGGER: MANUAL = 128-255[51%-100%]
CH7/PARAMETER #4	INTERVAL HIGH	Trigger: OFF = 0-127[0%-50%] Trigger: ON = 128-255[51%-100%]
CH8/PARAMETER #5	INTERVAL LOW	N/A
CH9/PARAMETER #6	PAUSE: OFF = 0-127[0%-50%] PAUSE: ON = 128-255[51%-100%]	N/A